

Certificate UK-G83 issue 2

The results of the G83/2 tests are summarized in this certificate.
 Omnik New Energy Co., Ltd declares that the units installed in UK market and set for G83/2 operations are characterized by the following features:

- The internal specification and parameters are set to be compliant with: Engineering Recommendation G83 issue 2, 2014.
- All units have internal parameters setting.
- These parameters cannot be changed by user, an installer or by any person other than the manufacturer.
- All units are tested before shipping according to: Engineering Recommendation G83 issue 2, 2014.

SSEG Type reference number	PHOTO-VOLTAIC Inverter		
SSEG Type	Omniksol-1k-TL2,Omniksol-1.5k-TL2,Omniksol-2k-TL2 Omniksol-2.5k-TL2,Omniksol-3k-TL2		
System Supplier name	Omnik New Energy Co.,Ltd.		
Address	CN-215213 Suzhou China Xinghu Road No. 218 Biobay Park A4-314		
Tel	+86 512 6956 8216	Fax	+86 512 6295 6682
E:mail	service@omnik-solar.com	Web site	www.omnik-solar.com

Maximum rated capacity	Connection Option	
	1	kW single phase (Omniksol-1k-TL2)
	1.5	kW single phase (Omniksol-1.5k-TL2)
	2	kW single phase (Omniksol-2k-TL2)
	2.5	kW single phase (Omniksol-2.5k-TL2)
	3	kW single phase (Omniksol-3k-TL2)
	NA	kW three phase
	NA	kW two phases in three phase system
	NA	kW two phases split phase system

SSEG manufacturer/supplier declaration

I certify on behalf of the company named above as a manufacturer/supplier of Small Scale Embedded Generators, that all products manufactured/supplied by the company with the above SSEG Type reference number will be manufactured and tested to ensure that they perform as stated in this Type Verification Test Report, prior to shipment to site and that no site modifications are required to ensure that the product meets all the requirements of G83/2.

Signed	2014-10-17	On behalf of	Omnik New Energy Co.,Ltd
---------------	------------	---------------------	--------------------------

UK-G83 issue 2 TEST RESULT DETAILS – TYPE VERIFICATION TEST SHEET

Omniksol-1k-TL2

Power Quality. Harmonics

SSEG rating per phase (rpp)		1	kW		NV=MV*3.68/rpp	
Harmonic	At 45-55% of rated output	100% of rated output				
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.010	0.0386	0.01	0.037	1.080	
3	0.130	0.4786	0.126	0.4635	2.300	
4	0.008	0.0281	0.006	0.022	0.430	
5	0.024	0.0899	0.014	0.0517	1.140	
6	0.010	0.0385	0.006	0.0238	0.300	
7	0.043	0.1590	0.034	0.1263	0.770	
8	0.007	0.0264	0.006	0.0207	0.230	
9	0.027	0.0990	0.02	0.0736	0.400	
10	0.012	0.0437	0.011	0.0395	0.184	
11	0.041	0.1499	0.035	0.1273	0.330	
12	0.007	0.0240	0.011	0.0398	0.153	
13	0.020	0.0740	0.017	0.0638	0.210	
14	0.006	0.0207	0.008	0.0311	0.131	
15	0.030	0.1122	0.022	0.0826	0.150	
16	0.008	0.0300	0.005	0.018	0.115	
17	0.014	0.0506	0.013	0.0492	0.132	
18	0.006	0.0225	0.003	0.0128	0.102	
19	0.025	0.0909	0.015	0.0552	0.118	
20	0.003	0.0106	0.003	0.0125	0.092	
21	0.014	0.0504	0.009	0.0342	0.107	0.160
22	0.004	0.0139	0.006	0.0208	0.084	
23	0.021	0.0785	0.012	0.0456	0.098	0.147
24	0.003	0.0118	0.002	0.0082	0.077	
25	0.011	0.0387	0.011	0.0422	0.090	0.135
26	0.004	0.0153	0.005	0.0174	0.071	
27	0.017	0.0610	0.009	0.0338	0.083	0.124
28	0.003	0.0099	0.002	0.0076	0.066	
29	0.009	0.0348	0.009	0.0317	0.078	0.117
30	0.002	0.0057	0.002	0.0078	0.061	
31	0.013	0.0491	0.007	0.0256	0.073	0.109
32	0.002	0.0063	0.001	0.0051	0.058	
33	0.007	0.0253	0.008	0.0293	0.068	0.102
34	0.002	0.0059	0.001	0.0028	0.054	
35	0.011	0.0415	0.005	0.0195	0.064	0.096
36	0.001	0.0052	0.001	0.0034	0.051	
37	0.006	0.0236	0.007	0.0243	0.061	0.091
38	0.001	0.0054	0.001	0.0045	0.048	
39	0.011	0.0397	0.004	0.0162	0.058	0.087
40	0.001	0.0044	0	0.0008	0.046	

Report Date: 2014-10-17 www.omnik-solar.com Page 1 of 10

File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate

This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd.
 It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only.
 Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216
 Fax +86 512 62956682

UK-G83 issue 2 TEST RESULT DETAILS – TYPE VERIFICATION TEST SHEET

Omniksol-1.5k-TL2

Power Quality. Harmonics

SSEG rating per phase (rpp)		1.5	kW		NV=MV*3.68/rpp		
Harmonic	At 45-55% of rated output	100% of rated output				Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps			
2	0.010	0.0253	0.011	0.0261	1.080		
3	0.128	0.3142	0.12	0.2937	2.300		
4	0.008	0.0202	0.005	0.0129	0.430		
5	0.016	0.0384	0.019	0.046	1.140		
6	0.009	0.0222	0.005	0.0131	0.300		
7	0.037	0.0916	0.029	0.0717	0.770		
8	0.008	0.0200	0.006	0.0143	0.230		
9	0.023	0.0554	0.018	0.0441	0.400		
10	0.010	0.0253	0.009	0.0232	0.184		
11	0.037	0.0919	0.025	0.0624	0.330		
12	0.010	0.0244	0.01	0.0238	0.153		
13	0.020	0.0495	0.014	0.0339	0.210		
14	0.005	0.0129	0.01	0.024	0.131		
15	0.025	0.0612	0.015	0.0366	0.150		
16	0.006	0.0155	0.002	0.0058	0.115		
17	0.016	0.0388	0.009	0.0214	0.132		
18	0.006	0.0139	0.003	0.008	0.102		
19	0.017	0.0421	0.01	0.024	0.118		
20	0.002	0.0056	0.006	0.0143	0.092		
21	0.010	0.0252	0.008	0.0208	0.107	0.160	
22	0.004	0.0103	0.007	0.0174	0.084		
23	0.014	0.0331	0.008	0.0204	0.098	0.147	
24	0.003	0.0085	0.003	0.0079	0.077		
25	0.012	0.0285	0.01	0.0257	0.090	0.135	
26	0.004	0.0101	0.004	0.0089	0.071		
27	0.010	0.0250	0.006	0.0148	0.083	0.124	
28	0.002	0.0040	0.004	0.0096	0.066		
29	0.009	0.0217	0.007	0.0166	0.078	0.117	
30	0.002	0.0056	0.003	0.0077	0.061		
31	0.008	0.0197	0.004	0.0109	0.073	0.109	
32	0.001	0.0031	0.001	0.0024	0.058		
33	0.008	0.0199	0.006	0.0154	0.068	0.102	
34	0.001	0.0032	0.001	0.0033	0.054		
35	0.006	0.0152	0.003	0.0071	0.064	0.096	
36	0.001	0.0027	0.001	0.0034	0.051		
37	0.007	0.0163	0.006	0.0147	0.061	0.091	
38	0.001	0.0022	0.002	0.0038	0.048		
39	0.005	0.0121	0.002	0.0056	0.058	0.087	
40	0.001	0.0032	0.001	0.0032	0.046		

Report Date: 2014-10-17 www.omnik-solar.com Page 1 of 10

File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate

This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd.
 It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only.
 Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216
 Fax +86 512 62956682

UK-G83 issue 2 TEST RESULT DETAILS – TYPE VERIFICATION TEST SHEET

Omniksol-2k-TL2

Power Quality. Harmonics

SSEG rating per phase (rpp)		2	kW		NV=MV*3.68/rpp	
Harmonic	At 45-55% of rated output	100% of rated output				
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.010	0.0180	0.011	0.0206	1.080	
3	0.127	0.2331	0.108	0.1995	2.300	
4	0.006	0.0102	0.007	0.0127	0.430	
5	0.014	0.0255	0.027	0.0495	1.140	
6	0.006	0.0112	0.005	0.0093	0.300	
7	0.031	0.0574	0.027	0.0495	0.770	
8	0.006	0.0114	0.005	0.0092	0.230	
9	0.019	0.0350	0.014	0.0252	0.400	
10	0.010	0.0183	0.004	0.0072	0.184	
11	0.032	0.0592	0.017	0.0311	0.330	
12	0.011	0.0209	0.008	0.0146	0.153	
13	0.017	0.0307	0.011	0.0198	0.210	
14	0.008	0.0146	0.008	0.0143	0.131	
15	0.020	0.0377	0.01	0.0187	0.150	
16	0.005	0.0083	0.006	0.0111	0.115	
17	0.012	0.0221	0.008	0.0156	0.132	
18	0.004	0.0083	0.002	0.0037	0.102	
19	0.015	0.0269	0.007	0.0135	0.118	
20	0.004	0.0066	0.004	0.0075	0.092	
21	0.008	0.0147	0.008	0.0147	0.107	0.160
22	0.005	0.0096	0.005	0.0084	0.084	
23	0.012	0.0220	0.006	0.0117	0.098	0.147
24	0.002	0.0045	0.008	0.0154	0.077	
25	0.011	0.0209	0.006	0.0108	0.090	0.135
26	0.005	0.0090	0.002	0.0034	0.071	
27	0.009	0.0165	0.005	0.0094	0.083	0.124
28	0.002	0.0033	0.004	0.0081	0.066	
29	0.009	0.0157	0.006	0.0105	0.078	0.117
30	0.002	0.0043	0.002	0.0035	0.061	
31	0.007	0.0125	0.004	0.0071	0.073	0.109
32	0.002	0.0036	0.001	0.0025	0.058	
33	0.008	0.0147	0.006	0.0106	0.068	0.102
34	0.001	0.0021	0.001	0.0023	0.054	
35	0.005	0.0093	0.002	0.0039	0.064	0.096
36	0.001	0.0020	0.001	0.0023	0.051	
37	0.006	0.0119	0.005	0.0091	0.061	0.091
38	0.001	0.0017	0.001	0.0022	0.048	
39	0.004	0.0071	0.002	0.0039	0.058	0.087
40	0.001	0.0017	0.002	0.0034	0.046	

Report Date: 2014-10-17 www.omnik-solar.com Page 1 of 10

File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate

This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd.
 It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only.
 Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216
 Fax +86 512 62956682

UK-G83 issue 2 TEST RESULT DETAILS – TYPE VERIFICATION TEST SHEET

Omniksol-2.5k-TL2

Power Quality. Harmonics

SSEG rating per phase (rpp)		2.5	kW		NV=MV*3.68/rpp		
Harmonic	At 45-55% of rated output	100% of rated output				Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps			
2	0.011	0.0160	0.013	0.0189	1.080		
3	0.124	0.1822	0.093	0.1369	2.300		
4	0.006	0.0085	0.009	0.0133	0.430		
5	0.018	0.0267	0.047	0.0695	1.140		
6	0.006	0.0091	0.009	0.0134	0.300		
7	0.031	0.0450	0.033	0.0492	0.770		
8	0.006	0.0088	0.007	0.0108	0.230		
9	0.019	0.0273	0.023	0.0336	0.400		
10	0.009	0.0138	0.003	0.0045	0.184		
11	0.029	0.0428	0.02	0.0301	0.330		
12	0.009	0.0134	0.005	0.0076	0.153		
13	0.017	0.0253	0.023	0.0336	0.210		
14	0.010	0.0142	0.005	0.0068	0.131		
15	0.017	0.0255	0.006	0.0089	0.150		
16	0.003	0.0038	0.01	0.014	0.115		
17	0.009	0.0139	0.017	0.0251	0.132		
18	0.003	0.0037	0.003	0.0046	0.102		
19	0.013	0.0188	0.004	0.0055	0.118		
20	0.006	0.0086	0.005	0.0071	0.092		
21	0.008	0.0120	0.012	0.0184	0.107	0.160	
22	0.007	0.0098	0.003	0.0045	0.084		
23	0.010	0.0141	0.004	0.0052	0.098	0.147	
24	0.003	0.0037	0.01	0.0154	0.077		
25	0.010	0.0150	0.011	0.0157	0.090	0.135	
26	0.005	0.0066	0.003	0.0049	0.071		
27	0.008	0.0113	0.003	0.0042	0.083	0.124	
28	0.004	0.0053	0.003	0.004	0.066		
29	0.008	0.0112	0.008	0.0123	0.078	0.117	
30	0.003	0.0040	0.002	0.003	0.061		
31	0.006	0.0084	0.004	0.0065	0.073	0.109	
32	0.001	0.0018	0.002	0.0026	0.058		
33	0.006	0.0095	0.007	0.0108	0.068	0.102	
34	0.001	0.0016	0.002	0.0027	0.054		
35	0.004	0.0065	0.004	0.0064	0.064	0.096	
36	0.002	0.0025	0.001	0.0021	0.051		
37	0.006	0.0087	0.006	0.0092	0.061	0.091	
38	0.002	0.0026	0.001	0.0021	0.048		
39	0.003	0.0047	0.004	0.0061	0.058	0.087	
40	0.001	0.0016	0.002	0.0023	0.046		

Report Date: 2014-10-17 www.omnik-solar.com Page 1 of 10

File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate

This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd.
 It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only.
 Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216
 Fax +86 512 62956682

UK-G83 issue 2 TEST RESULT DETAILS – TYPE VERIFICATION TEST SHEET

Omniksol-3k-TL2

Power Quality. Harmonics

SSEG rating per phase (rpp)		3	kW		NV=MV*3.68/rpp	
Harmonic	At 45-55% of rated output	100% of rated output				
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2	0.011	0.0138	0.016	0.0202	1.080	
3	0.121	0.1488	0.073	0.09	2.300	
4	0.006	0.0069	0.01	0.0123	0.430	
5	0.022	0.0270	0.069	0.0841	1.140	
6	0.007	0.0083	0.012	0.0144	0.300	
7	0.029	0.0355	0.04	0.0486	0.770	
8	0.006	0.0077	0.01	0.0118	0.230	
9	0.019	0.0227	0.025	0.0308	0.400	
10	0.009	0.0116	0.008	0.01	0.184	
11	0.024	0.0295	0.024	0.0298	0.330	
12	0.010	0.0127	0.008	0.0104	0.153	
13	0.014	0.0166	0.024	0.0297	0.210	
14	0.009	0.0106	0.008	0.0101	0.131	
15	0.014	0.0168	0.007	0.0083	0.150	
16	0.004	0.0047	0.015	0.0183	0.115	
17	0.008	0.0104	0.02	0.0244	0.132	
18	0.004	0.0047	0.009	0.011	0.102	
19	0.010	0.0118	0.004	0.0045	0.118	
20	0.005	0.0058	0.007	0.008	0.092	
21	0.009	0.0116	0.013	0.016	0.107	0.160
22	0.005	0.0061	0.007	0.0091	0.084	
23	0.008	0.0092	0.004	0.0046	0.098	0.147
24	0.004	0.0053	0.004	0.0054	0.077	
25	0.010	0.0122	0.011	0.0131	0.090	0.135
26	0.005	0.0064	0.01	0.0126	0.071	
27	0.006	0.0076	0.002	0.0023	0.083	0.124
28	0.003	0.0038	0.005	0.006	0.066	
29	0.006	0.0077	0.008	0.0096	0.078	0.117
30	0.002	0.0028	0.003	0.004	0.061	
31	0.005	0.0058	0.003	0.0037	0.073	0.109
32	0.001	0.0015	0.005	0.0059	0.058	
33	0.006	0.0072	0.007	0.0088	0.068	0.102
34	0.001	0.0013	0.002	0.0025	0.054	
35	0.003	0.0042	0.003	0.0037	0.064	0.096
36	0.001	0.0016	0.004	0.005	0.051	
37	0.006	0.0075	0.007	0.0083	0.061	0.091
38	0.001	0.0011	0.004	0.005	0.048	
39	0.003	0.0031	0.003	0.0034	0.058	0.087
40	0.001	0.0013	0.003	0.0038	0.046	

Report Date: 2014-10-17 www.omnik-solar.com Page 1 of 10

File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate

This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd.
 It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only.
 Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216
 Fax +86 512 62956682

Omniksol-1k-TL2								
Power Quality. Voltage fluctuations and Flicker.								
	Starting			Stopping			Running	
	d_{max}	d_c	$d_{(t)}$	d_{max}	d_c	$d_{(t)}$	P_{st}	P_{It} 2 hours
Measured Values	0.55	0.21	0.0	0.55	0.21	0.0	0.064	0.064
Normalised to standard impedance and 3.68kW for multiple units	2.02	0.77	0	2.02	0.77	0	0.236	0.236
Limits set under BS EN 61000-3-2	4%	3.3%	3.3% 500ms	4%	3.3%	3.3% 500ms	1.0	0.65
Test start date		2014-10-13			Test end date		2014-10-17	
Test location		Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314						

Omniksol-1.5k-TL2								
Power Quality. Voltage fluctuations and Flicker.								
	Starting			Stopping			Running	
	d_{max}	d_c	$d_{(t)}$	d_{max}	d_c	$d_{(t)}$	P_{st}	P_{It} 2 hours
Measured Values	0.55	0.21	0.0	0.55	0.21	0.0	0.064	0.064
Normalised to standard impedance and 3.68kW for multiple units	1.35	0.52	0	1.35	0.52	0	0.157	0.157
Limits set under BS EN 61000-3-2	4%	3.3%	3.3% 500ms	4%	3.3%	3.3% 500ms	1.0	0.65
Test start date		2014-10-13			Test end date		2014-10-17	
Test location		Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314						

Report Date: 2014-10-17	www.omnik-solar.com	Page 1 of 10
File: Omniksol_1k&1.5k&2k&2.5k&3k-TL2_G83-2 Certificate		
This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd. It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only. Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216 Fax +86 512 62956682		

Omniksol-2k-TL2								
Power Quality. Voltage fluctuations and Flicker.								
	Starting			Stopping			Running	
	d_{max}	d_c	$d(t)$	d_{max}	d_c	$d(t)$	P_{st}	P_{lt} 2 hours
Measured Values	0.55	0.21	0.0	0.55	0.21	0.0	0.064	0.064
Normalised to standard impedance and 3.68kW for multiple units	1.01	0.39	0	1.01	0.39	0	0.118	0.118
Limits set under BS EN 61000-3-2	4%	3.3%	3.3% 500ms	4%	3.3%	3.3% 500ms	1.0	0.65
Test start date	2014-10-13			Test end date	2014-10-17			
Test location	Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314							

Omniksol-2.5k-TL2								
Power Quality. Voltage fluctuations and Flicker.								
	Starting			Stopping			Running	
	d_{max}	d_c	$d(t)$	d_{max}	d_c	$d(t)$	P_{st}	P_{lt} 2 hours
Measured Values	0.55	0.21	0.0	0.55	0.21	0.0	0.064	0.064
Normalised to standard impedance and 3.68kW for multiple units	1.01	0.39	0	1.01	0.39	0	0.118	0.118
Limits set under BS EN 61000-3-2	4%	3.3%	3.3% 500ms	4%	3.3%	3.3% 500ms	1.0	0.65
Test start date	2014-10-13			Test end date	2014-10-17			
Test location	Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314							

Omniksol-3k-TL2								
Power Quality. Voltage fluctuations and Flicker.								
	Starting			Stopping			Running	
	d_{max}	d_c	$d_{(t)}$	d_{max}	d_c	$d_{(t)}$	P_{st}	P_{lt} 2 hours
Measured Values	0.55	0.21	0.0	0.55	0.21	0.0	0.064	0.064
Normalised to standard impedance and 3.68kW for multiple units	1.01	0.39	0	1.01	0.39	0	0.118	0.118
Limits set under BS EN 61000-3-2	4%	3.3%	3.3% 500ms	4%	3.3%	3.3% 500ms	1.0	0.65
Test start date	2014-10-13			Test end date	2014-10-17			
Test location	Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314							

Omniksol-1k-TL2			
Power quality. DC injection.			
Test power level	10%	55%	100%
Recorded value	0.00875	0.01201	0.01172
as % of rated AC current	0.151%	0.207%	0.202%
Limit	0.25%	0.25%	0.25%

Omniksol-1.5k-TL2			
Power quality. DC injection.			
Test power level	10%	55%	100%
Recorded value	0.01497	0.04130	0.01593
as % of rated AC current	0.166%	0.157%	0.177%
Limit	0.25%	0.25%	0.25%

Omniksol-2k-TL2			
Power quality. DC injection.			
Test power level	10%	55%	100%
Recorded value	0.02122	0.01543	0.01713
as % of rated AC current	0.193%	0.140%	0.156%
Limit	0.25%	0.25%	0.25%

Omniksol-2.5k-TL2			
Power quality. DC injection.			
Test power level	10%	55%	100%
Recorded value	0.01555	0.01623	0.00876
as % of rated AC current	0.001%	0.001%	0.001%
Limit	0.25%	0.25%	0.25%

Omniksol-3k-TL2			
Power quality. DC injection.			
Test power level	10%	55%	100%
Recorded value	0.02921	0.01591	0.02274
as % of rated AC current	0.208%	0.113%	0.162%
Limit	0.25%	0.25%	0.25%

Omniksol-1k-TL2				
Power Quality. Power factor.				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.9957	0.9956	0.9940	
Limit	>0.95	>0.95	>0.95	

Omniksol-1.5k-TL2				
Power Quality. Power factor.				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.9978	0.9978	0.0070	
Limit	>0.95	>0.95	>0.95	

Omniksol-2k-TL2				
Power Quality. Power factor.				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.9986	0.9986	0.9982	
Limit	>0.95	>0.95	>0.95	

Omniksol-2.5k-TL2				
Power Quality. Power factor.				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.9989	0.9990	0.9987	
Limit	>0.95	>0.95	>0.95	

Omniksol-3k-TL2				
Power Quality. Power factor.				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.9990	0.9991	0.9990	
Limit	>0.95	>0.95	>0.95	

Omniksol-1k&1.5k&2k&2.5k&3k-TL2						
Protection. Frequency tests.						
Function	Setting		Trip test		"No trip tests"	
	Frequency	Time delay	Frequency	Time delay	Frequency/time	Confirm no trip
U/F stage 1	47.5Hz	20s	47.50Hz	19.91s	47.7Hz/ 25s	No trip
U/F stage 2	47Hz	0.5s	47.00Hz	0.509s	47.2Hz/ 19.98s	No trip
					46.8Hz/ 0.48s	No trip
O/F stage 1	51.5Hz	90s	51.50Hz	90.44s	51.3Hz/ 95s	No trip
O/F stage 2	52Hz	0.5s	52.00Hz	0.499s	51.8Hz/ 89.98s	No trip
					52.2Hz/ 0.48s	No trip

Omniksol-1k&1.5k&2k&2.5k&3k-TL2						
Protection. Voltage tests.						
Function	Setting		Trip test		"No trip tests"	
	Voltage	Time delay	Voltage	Time delay	Voltage/ time	Confirm no trip
U/V stage 1	200.1V	2.5s	200.0V	2.51s	204.1V/ 3.5s	No trip
U/V stage 2	184V	0.5s	183.9V	0.512s	188V/ 2.48s	No trip
					180V/ 0.48s	No trip
O/V stage 1	262.2V	1.0s	262.1V	1.01s	258.2V/ 2.0s	No trip
O/V stage 2	273.7V	0.5s	273.5V	0.497s	269.7V/ 0.98s	No trip
					277.7V/ 0.48s	No trip

Omniksol-1k-TL2						
Protection. Loss of Mains test.						
Note: Inverter tested according to BS EN 62116.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	248ms	214ms	353ms	334ms	361ms	351ms

Omniksol-1.5k-TL2						
Protection. Loss of Mains test.						
Note: Inverter tested according to BS EN 62116.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	237ms	222ms	330ms	342ms	387ms	371ms

Omniksol-2k-TL2						
Protection. Loss of Mains test.						
Note: Inverter tested according to BS EN 62116.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	205ms	200ms	393ms	346ms	348ms	339ms

Omniksol-2.5k-TL2						
Protection. Loss of Mains test.						
Note: Inverter tested according to BS EN 62116.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	211ms	206ms	376ms	356ms	362ms	349ms

Omniksol-3k-TL2						
Protection. Loss of Mains test.						
Note: Inverter tested according to BS EN 62116.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	209ms	218ms	388ms	367ms	358ms	353ms

Omniksol-1k&1.5k&2k&2.5k&3k-TL2				
Protection. Frequency change, Stability test.				
	Start Frequency	Change	End Frequency	Confirm no trip
Positive Vector Shift	49.5Hz	+9 degrees		No trip
Negative Vector Shift	50.5Hz	- 9 degrees		No trip
Positive Frequency drift	49.5Hz	+0.19Hz/sec	51.5Hz	No trip
Negative Frequency drift	50.5Hz	-0.19Hz/sec	47.5Hz	No trip

Fault level contribution.					
Omniksol-1k-TL2			Omniksol-1.5k-TL2		
For a Inverter SSEG			For a Inverter SSEG		
Time after fault	Volts	Amps	Time after fault	Volts	Amps
20ms	38.9	0.199	20ms	38.6	0.204
100ms	38.9	0.198	100ms	38.6	0.199
250ms	39.1	0.198	250ms	38.7	0.198
500ms	39.0	0.198	500ms	38.8	0.199
Time to trip	0.013	In seconds	Time to trip	0.007	In seconds
Omniksol-2k-TL2			Omniksol-2.5k-TL2		
For a Inverter SSEG			For a Inverter SSEG		
Time after fault	Volts	Amps	Time after fault	Volts	Amps
20ms	39.1	0.206	20ms	38.7	0.202
100ms	39.1	0.199	100ms	38.6	0.200
250ms	39.3	0.198	250ms	38.9	0.199
500ms	39.2	0.200	500ms	39.0	0.199
Time to trip	0.006	In seconds	Time to trip	0.007	In seconds
Omniksol-3k-TL2					
For a Inverter SSEG					
Time after fault	Volts	Amps			
20ms	39.1	0.200			
100ms	38.9	0.199			
250ms	39.0	0.199			
500ms	39.0	0.199			
Time to trip	0.010	In seconds			

Omniksol-1k&1.5k&2k&2.5k&3k-TL2					
Protection. Re-connection timer.					
Test proves that the reconnection sequence starts after a minimum delay of 20 seconds for restoration of voltage and frequency to within the stage 1 settings of table 1 of the subject normative.					
Time delay setting	Measured delay	No reconnection when voltage or frequency is brought to just outside stage 1 limits of table 1.			
20s	31s	At 266.2V	At 196.1V	At 47.4Hz	At 51.6Hz
Confirmation that the SSEG does not re-connect.		No reconnection	No reconnection	No reconnection	No reconnection

Omniksol-1k&1.5k&2k&2.5k&3k-TL2
Self-Monitoring solid state switching.
It has been verified that in the event of the solid state switching device failing to disconnect the SSEG, the voltage on the output side of the switching device is reduced to a value below 50 volts within 0.5 seconds.

---- End of Document ----

Report Date: 2014-10-17	www.omnik-solar.com	Page 1 of 10
File: Omniksol_1k&1.5k&2K&2.5k&3k-TL2_G83-2 Certificate		
This document and the contents herein are the confidential property of Omnik New Energy Co.,Ltd. It shall not be reproduced, changed, or altered in any way and is for the internal use of Omnik only. Omnik New Energy Co.,Ltd, CN-215213 Suzhou China Xinghu Road No.218 Biobay Park A4-314 – Phone +86 512 6956 8216 Fax +86 512 62956682		